



CRONUS ATS PRO THERMAL SCOPE

35-400 | 50-640



USER MANUAL

athlonoptics.com

CONTENTS

DISCLAIMERS	1
IMPORTANT INSTRUCTIONS	1
CAUTIONS	2
CHAPTER 1 - PRODUCT INTRODUCTION	3
CHAPTER 2 - STORAGE AND TRANSPORTATION	3
CHAPTER 3 - LIST OF ITEMS	4
CHAPTER 4 - TECHNICAL SPECIFICATION	5
CHAPTER 5 - PRODUCT COMPONENTS	9
CHAPTER 6 - OPERATION INSTRUCTION	10
6.1 Quick start	10
6.1.1 USB Type C & Micro HDMI	10
6.1.2 Power Supply	10
6.1.3 Language Settings	11
6.1.4 Focusing	12
6.2 Button Description	13
6.2.1 Power Button	14
6.2.2 Menu Knob	15
6.2.3 M Button	15
6.2.4 Zoom Knob	16
6.2.5 Shutter Button	17
CHAPTER 7 - FUNCTION DESCRIPTION	18
7.1 Home Screen List	18
7.2 Shortcut Menu	19
7.3 Main Menu Operation	23
7.4 One Shot Zero Calibration	37
CHAPTER 8 - RETICLE DESCRIPTION	38
CHAPTER 9 - BALLISTICS APP	40
CHAPTER 10 - OTHER INSTRUCTIONS	43
10.1 Power Display	43
10.2 Software Connection	43
CHAPTER 11 - FIRMWARE UPDATE	46
11.1 Update Via APP	46
11.2 Update Via Computer	47
CHAPTER 12 - COMMON TROUBLESHOOTING GUIDE	48
PRODUCT WARRANTY CARD	49

DISCLAIMERS

This product is for civilian use only and shall not be used for infringing the rights of third parties, medical, safety equipment or other applications where product failure may cause danger to life or personal injury. In the event of a conflict between the foregoing and applicable law, the law shall prevail.

IMPORTANT INSTRUCTIONS

This manual is a general manual for a series of products, which means that the product of a specific model you receive might differ from the picture herein. Please refer to the actual product received.

This user manual is prepared for the convenience of users to use and know our products. We have tried our best to ensure the accuracy of its contents, but we are still unable to guarantee its completeness since our products can be continuously updated and upgraded. Athlon Optics reserves the right to modify the manual at any time without notice.

CAUTIONS

DANGER

- 1) Please charge the battery with the method described in this guide and follow the charging procedure and precautions. Improper battery charging will cause heating, damage and even physical injury.
- 2) Do not try to open or disassemble the battery at any time.
- 3) The internal battery can only be charged through the USB-C port and the external battery does not charge the internal battery. The optic draws current from external battery first and the internal battery when external one runs out power.

WARNING

- 1) This scope contains advanced electronics. To prolong the life of this optic, avoid any undue physical damage or violent actions.
- 2) Do not use or store the equipment in an environment that exceeds the allowable operating or storage temperature.
- 3) Do not directly aim the equipment at high-intensity thermal radiation sources, such as the sun, lasers, spot welding machines, etc.
- 4) Avoid allowing debris to enter any ports in this optic.
- 5) Do not knock, throw or vibrate instruments and accessories to avoid damage.
- 6) Any modification, alterations or attempts to disassemble this scope will void the user's warranty. All repairs must be made through Athlon Optics.
- 7) Avoid contaminating this scope with oils or solvents.
- 8) Please observe the following measures when wiping this Scope:
 - Non-optical surface: Use a clean and soft cloth to wipe the non-optical surface of the thermal scope.
 - Optical surface: When using the thermal scope, avoid contaminating the optical lens surfaces of this scope. Avoid touching the objective lens with your hands. Oils and solvents can degrade the lens coatings. When the surface of the optical lens is polluted, use special lens paper to wipe it carefully.
- 9) Do not place the battery in a high temperature or near a high-temperature object.
- 10) Do not short circuit the positive and negative poles of the battery.
- 11) Do not expose the battery to moisture or water.
- 12) Only use the original chargers and adapters provided with this scope.

CHAPTER 1 - PRODUCT INTRODUCTION

Athlon Optics thermal scope retains the appearance of a traditional daylight scope and perfectly incorporates latest premium thermal imaging technology. The design of this scope accommodates traditional hunters' habits of handling the scope and rifle. ATS series adopts 400x300/640x480 12 μ m high-sensitivity thermal detector with two different lens options of 35mm, 50mm, and its 10 sets of zero profiles that make it convenient to switch between different calibers of rifles.

CHAPTER 2 - STORAGE AND TRANSPORTATION

In order to prevent danger and property loss, please read this manual carefully before using the scope and strictly abide by it during its use.


STORAGE

- 1) The packaged product shall be stored in well-ventilated and clean rooms at -22°F ~ 122°F (-30°C - 50°C), without condensing or corrosive gas, under relative humidity of no more than 95%.
- 2) Please regularly charge it every 3 months.


TRANSPORTATION

The product shall be protected from rain and water. This optic contains advanced electronics. To prolong the life of this optic, avoid any undue physical damage or violent actions.


CHAPTER 3 - LIST OF ITEMS




PLUG



PICATINNY
COMPATIBLE




POWER
ADAPTER




CHARGER




EXTERNAL
BATTERY



MICRO HDMI
CABLE




BAG



TYPE-C CABLE

Optional:



REMOTE CONTROL

CHAPTER 4 - TECHNICAL SPECIFICATION

Product Name		Thermal Imaging Riflescope	
Model		35 - 400 PRO	50 - 640 PRO
Detector	Total Resolution	400×300 @12μm	640×480 @12μm
	Scope Material	Aluminum	
	Effective Resolution	400×300	640×480
	Spectral	8-14μm	
Lens	Focal length	35mm F1.0	50mm F1.0
	Focusing	Manual	
	FOV	7.8° × 5.9°	8.8° × 6.6°
Image	Frame Rate	50Hz	
	Electronic Amplification	1x - 4x	1x - 8x
Power	Battery	1 Built-in Battery, and 2 Spare External Batteries	
	Charging	Chargeable, USB-C	
Scope Interface	USB	USB-C (2.0) can power the Scope and charge both internal and external battery; can transmit data	
	Video Interface	Micro HDMI	
	WIFI	Realtime video transmission, 2.4G frequency range,	
	Bluetooth	Bluetooth remote control, which can connect to Scope for wireless control	
	External Extension	External monitor through USB-C	
	Tube Diameter	30mm	


Product Name		35 - 400 PRO	50-640 PRO
Display System	OLED	0.49 Inches OLED	
	Resolution	1440x1080, Full screen display	
	Diopter	-4 - +4	
	Distance of exit pupil	48mm	
	Diameter of exit pupil	8mm	
	Eyepiece magnification	14×	
	Scope Magnification	3.3 - 13.2x	2.95 - 23.66x
	Video Output Standard	HDMI	
Button	Power on/off	Yes	
	Menu knob (pressable)	Yes	
	Photo/Recording	Yes	
	Zoom-in knob	Yes	
Function	Linear Magnifying	Yes	
	Screen Brightness	10 levels	
	Detector Brightness	10 levels	
	Detector Contrast	10 levels	
	Image Enhancement	Yes	
	Scene Mode	Natural, Enhanced, Highlight	
	Stadiametric Rangefinder	Yes	
	Eco Mode	Yes	
	Photo Capturing	Yes	
	Video Recording	Yes, through both Scope and APP	

Product Name		35-400 PRO	50-640 PRO
Function (Continued)	Video Recording with Audio	Yes	
	Color Palettes	White Hot, Black Hot, Red Hot, Green Hot, Iron Red, Blue Hot, Sepia	
	Hotspotting Track	Yes	
	Compensation Mode	Shutter Compensation	
	Automatic Power-off	Off, Automatic power-off in 15/30/60 minutes	
	Auto Sleep	Off, Auto sleep in 5/10/15 minutes	
	Charging Indicator Light	Light that indicates if scope is charging	
	Language Settings	English/French/German/Italian/Spanish	
	Time Settings	Yes	
	Watermark Settings	Yes	
	PIP	Upper Left/Upper Middle/Upper Right, Closed	
	Restore Default	Yes	
	Internal Memory	Yes, can be formatted (128GB capacity)	
	Unit of Measurement	Meter/Yard	
	Bluetooth	Yes	
	Zero Setting	50m/100m/200m/300m/500m 50y/100y/200y/300y/500y	
	Reticle type	10 types in total	
	Reticle color	Black/White/Yellow/Green/Red/Blue	
	Reticle Brightness	10 levels	
	One Shot - Zero in	Yes	
	Built-in Ballistic Calculator	Yes	
	Firmware Upgrade	Yes	

Product Name		35 - 400 PRO	50 - 640 PRO
System	Power-on Time	≤12s@77°F ≤12s@25°C	
Environment Adaptation	Working Temperature	-22°F ~ 122°F (external power supply only below -4°F) -30°C ~ 50°C (external power supply only below -20°C)	
	Storage Temperature	-49°F ~ 158°F -45°C ~ 70°C	
	Humidity	10% - 95% no condensing	
	Impact	800G/1ms	
	Vibration	10Hz - 150Hz - 10Hz 0.15mm IEC60068-2-6	
	Dust-proof / Water-proof	IP67	
	Certificate	RoHS, CE, FCC, UKAC, UN 38.8	
Package	Items Included	Thermal Scope, USB-C cable, Eyepiece Rubber Cover, 5V2A adapter (US/EU/AU/EU), External Battery ×2, Battery charger, micro HDMI video cable, Scope Ring, Manual, Warranty Card	
	Color	Black	
	Weight	37.4 oz	
	Dimensions	14.3" x 4.2" x 2.35"	14.7" x 4.2" x 2.35"

CHAPTER 5 - PRODUCT COMPONENTS

This manual is applicable to many models of this series, and the illustration may not perfectly match your product.



CHAPTER 6 - OPERATION INSTRUCTION

6.1 QUICK START


6.1.1 USB TYPE C & MICRO HDMI

USB-C PORT:

The external port with USB cable can be connected to the external power supply to charge the product. The output of the external power supply is 5V2A.

MICRO HDMI

A micro HDMI to HDMI cable can be connected to the optic to provide a live feed to an external monitor equipped with HDMI.




6.1.2 POWER SUPPLY

POWER CHARGING:



When using the product for the first time, be sure to charge the Scope for at least 4 hours. When charging, please leave the USB cover open, use the provided Type C USB charging cable and power adapter. The charging indicator light stays red, then turns green when charging is completed.

BATTERY COVER:

To install or remove the battery, please remove the battery cover on the right side. Please insert the battery in the direction shown in the figure, do not force the battery in.




6.1.3 LANGUAGE SETTINGS



When the scope is powered on for the first time to select the language, rotate the "Menu Knob" to scroll up and down to select the language; Short press the "M Button" to confirm the language selection and jump to the Home interface; long press The "M Button" to return to the language scrolling selection.

6.1.4 FOCUSING




DIOPTER ADJUSTMENT:

After the thermal scope is powered on, rotate the diopter adjustment knob to correct differences for each individual's eye sight until a clear image is observed.

FOCUS:


After the thermal scope is powered on, rotate the focus ring until the target image becomes clear. Repeat this step when distance to the target changes.

6.2 BUTTON DESCRIPTION



Button	Current device status	Rotation	Short Press	Long Press
Power Button	Power on	/	Compensation	Display on/off
	Power off	/	/	Power on
	Display off	/	Display on	/
Menu Knob	Menu bar not shown	Switch to color palettes	/	/
	Menu bar displayed	Toggle options	/	/
M Button	Menu bar not shown	/	Shortcut menu	Menu
	Menu bar displayed	/	Select current option	Return to previous option
Zoom Knob	Menu bar not shown	Zoom	/	/
		/	Quick Zoom	Holdover distance menu

6.2.1 POWER BUTTON



POWER ON▪

Long press and hold the power button until the startup picture appears in the eyepiece. If internal battery is completely discharged, the device can not be turned on with external battery only. It can be turned on with the included power adapter through USB-C port.

POWER OFF▪

a. Manual power-off: long press and hold the power button, the power-off progress bar will be displayed, and the power-off is completed after the progress bar is finished.

b. Automatic power-off: in the set automatic power-off time, without any button operation, the scope will power down.

DISPLAY ON▪

In display off mode, press any button to wake the screen.


DISPLAY OFF▪

Press and hold the power button, the progress bar of power-off will be displayed. Before the progress bar is finished, release the power-off button to cancel the power off process and activate the display off mode.

COMPENSATION▪

When it is turned on and the menu is not activated, short-press the power on/off button to refresh the thermal sensor. Two Compensation modes, manual and automatic, can be set through the Main Menu.

6.2.2 MENU KNOB




QUICK COLOR PALETTE SWITCHING▪

When the scope is turned on and the menu is not activated, turn the menu knob to switch between white hot, black hot, red hot, iron red, blue hot, green hot, and sepia color.

MENU MOVEMENT▪

When the menu is activated, turn the menu knob clockwise to move menu or option down/to the right; Turn the knob counterclockwise to move menu or option up/to the left.

6.2.3 M BUTTON



SHORTCUT MENU▪

When it is powered on and the menu is not activated, short-press the "M" button, and the shortcut menu option will appear.


MAIN MENU

Main menu option is activated by long-pressing the "M" button.

CONFIRM AND BACK/EXIT

When it is powered on and the menu is activated, short-press the "M" button to confirm the current selection and return to the previous menu; Press and hold the "M" button to return to or exit the menu without saving the current settings.

6.2.4 ZOOM KNOB



ZOOM-IN

When it is turned on, rotate the zoom knob counter-clockwise to enlarge the image in 0.1X steps, and zooming stops when the maximum magnification is reached.


ZOOM-OUT

When it is turned on, rotate the zoom knob clockwise to shrink the image by 0.1X, and stop when it reaches the minimum value.

QUICK ZOOM

The quick zoom can be obtained by short-pressing the button on the zoom knob.

6.2.5 SHUTTER BUTTON



TAKE PHOTOS


When it is turned on, rotate the zoom knob counter-clockwise to enlarge the image in 0.1X steps, and zooming stops when the maximum magnification is reached.

VIDEO RECORDING

When it is turned on, rotate the zoom knob clockwise to shrink the image by 0.1X, and stop when it reaches the minimum value.

CHAPTER 7 - FUNCTION DESCRIPTION


7.1 HOME SCREEN LIST



- 1) PIP: left top, middle top, right top display
- 2) Recording duration
- 3) Magnification power
- 4) Video Recording Failed
- 5) Compensation Mode Indicator
- 6) Video Recording Successful
- 7) Audio Input Indicator
- 8) WiFi connected
- 9) Bluetooth on
- 10) Auto-shot Record
- 11) Eco-mode on
- 12) Battery capacity indication
- 13) Ballistic Calculator Indicator
- 14) Zero in distance / Zero profile
- 15) Internal memory full warning
- 16) USB Mode
- 17) Serial Port Connection Mode
- 18) Date
- 19) Time
- 20) Ranging Angle Indication

7.2 SHORTCUT MENU


When the power is turned on and the menu is not activated, short press the "M Button" to display the shortcut menu options.



21 COLOR PALETTES




Switch among seven color palettes (white hot, black hot, red hot, iron red, blue hot, green hot, and sepia).



22 PIP




Choose from top left, top middle, and top right positions.



23 SCREEN BRIGHTNESS



1-10 Screen Brightness level can be adjusted.



24 WIFI



WiFi can be used to transmit real-time video to the mobile phone after the mobile phone is connected to your device, and the device can be operated through the Athlon Thermal APP to access the photos/videos of the device; photos/videos can be played, shared, deleted, etc.


NOTE: Search and download Athlon Thermal APP in the mobile phone APP store, open the APP, find the WiFi name 'Cronus ATS PRO XX-XXX' in the settings of mobile phone WiFi, and enter the password '12345678', to start remote operation after successful connection.



25 HOT TRACK




A white cross cursor is displayed when it is turned on to trace the highest temperature point in the full image.



26 ECO MODE





After being turned on, the scope will switch to power-saving mode, under which OLED brightness will be fixed to 20% and cannot be adjusted, and WIFI will not be turned on. If the current WIFI is already on, WIFI will be turned off, and the shooting record function cannot be turned on. If you are currently in shooting recording mode, the prompt is turned off.



27 STADIAMETRIC RANGEFINDING



The position of the lower horizontal line remains unchanged and rotate the Menu knob to move the upper horizontal line until the spacing between the two lines is equal to the image height of the target. The distance from the target can be estimated by referring to the approximate ranging values of the four animals (rabbit - 14", coyote - 21", wild boar - 30", and deer - 36") in the upper left corner.




28 ZERO CALIBRATION




The preset zero distances under the profile selected in the main menu must match zero calibration in short menu.

NOTE: Only select the distances that have been zeroed, and do not select the distance still set at default factory x/y value (0,0).




7.3 MAIN MENU OPERATION


After scope is turned on, long press M Button to activate main menu, exit, and go back to main category level after saving a setting change. Short Press M Button to select a category or a setting, and save changes and exit a setting. Rotate Menu Knob to cycle through categories, individual settings, and values of individual settings. Main menu stays on and turns off if no any input is made within 12 seconds, long press M Button to reactivate it.




29 BALLISTIC SOLUTION



Ballistic Calculator: Ballistic profiles must be created in the Athlon Ballistics APP first. Long press zoom button to set holdover distances. Holdover points for up to 4 different distances can be adjusted through this menu.




Angular Measurement: Select between MOA and MIL units of measurement.




Brightness: Brightness can be adjusted within 1-10 levels.

NOTE: The value of adjusted brightness will be saved in the current scene mode.




30 IMAGE QUALITY ADJUSTMENT



Contrast: Contrast can be adjusted within 1-10 levels.

NOTE: The value of adjusted contrast will be saved in the current scene mode.



Scene Mode: Three scene modes, natural/enhanced/highlight, can be set.








Image Enhancement: Turn on to enhance the image quality.




Compensation Mode: Shutter Mode can be set through the Main Menu. Scene Mode sets short pressing the power button to capture an even temperature surface to refresh the thermal sensor. The best way to perform Scene Mode compensation is doing it with the lens cap closed. Shutter Mode sets short pressing the power button to close the device shutter and create an even temperature surface to refresh the thermal sensor.




Reticle Type: 10 reticle types in total can be selected.




Reticle Color: Can be selected in black/white/yellow/green/blue/red.




Profile Configuration: 10 groups of zeroing profiles, from A-J can be saved. The zeroing distance, zeroing location, reticle type, reticle color and reticle brightness are saved for each profile.





Reticle Brightness: Can be adjusted within 1-10 levels.







Zeroing Settings: This is the user interface for one-shot zeroing. 50/100/200/300/500 yards or meters can be selected for zeroing under each group of profiles. After zero is set, use the shortcut menu to select the preset zero distance under each profile.




Audio Input: When the microphone is turned on, you can record audio while recording video, so that the sound is integrated into the video files.




Auto-Shot Record: When this function is turned on, it will automatically record a video and 5 images when the user shoots (video: 3 seconds before shooting ~ 7 seconds after shooting). If a shot is made within the 7 seconds, the device will continue recording for 30 minutes.




Auto-Shot Sensitivity: Shooting trigger sensitivity, divided into 1-5 settings; the 5th setting is the most sensitive setting.




Manual Record Clip Duration: 15/60 second clip duration can be selected to automatically end video recording within the time selected.




Watermark Settings: Support time and date.




34 POWER SETTINGS




Auto Sleep: The Auto Sleep time can be set to 5/10/15 min. If there is no operation within the set time, the scope will enter sleep mode.




Auto Power-Off: The automatic Power-off time can be set to 15/30/60 minutes. If there is no operation within the set time, the power-off will be activated, and the scope will be powered off.




Timed Menu off: the menu can be turned off automatically within 10/20/60 seconds.



Charging Indication: Switch that turns On/Off the charging port indication light





Language Settings: Available in English/French/German/Italian/Spanish




35 LOCAL SETTINGS


Unit Measurement: yard or meter




Time Formats: selectable between 12H / 24H





Date Formats:
Optional from:
MM-DD-YYYY
YYYY-MM-DD
DD-MM-YYYY




Black Screen Indication: black screen indication icon can be turned on and off




Time Setup: Enter the Time Setup, rotate the Menu knob to move among different options, and press the "M" button to enter the next level adjustment, and then rotate the Menu knob to move between the specific time values



Bluetooth: Can be turned on and off




Memory Capacity: free memory capacity/total capacity




Memory Formatting: Select Memory Formatting. Select "Confirm" to confirm formatting, and select "Cancel" to cancel the operation

⚠ SELECT WITH CAUTION!






Restore Default: You can choose to restore the factory settings. Select "Confirm" to restore all parameters to factory settings; Select "Cancel" to cancel the operation

⚠ SELECT WITH CAUTION!



About: Check the current device in the APP version number and MAC address




7.4 ONE SHOT ZERO CALIBRATION

To sight in the rifle to your zero position please follow the steps as below:


Go to Zeroing Settings interface via the main menu to start zeroing in process. Aim the reticle center to the center of the target, and hold the rifle as stable as possible and fire a bullet. Rotate the menu knob to turn on the freeze option in the pop-up window showing "X" and "Y" while making sure the light green X (cross cursor) still pointing at the center of target.

After the image is frozen, short press M Button and then rotate the Menu knob to select and adjust the value of "X" (move left and right) or "Y" (move up and down) to move the center of the reticle until it overlaps with the actual point of impact. Use menu knob to select the "Confirm" option in the Pops up window, and short press the M button to confirm it. Each rotation of the Menu knob moves the center of the reticle by 1px. The cross cursor represents the original aiming point before any adjustment was made.Each rotation of the Menu knob moves the center of the reticle by 1px. The cross cursor represents the original aiming point before any adjustment was made.

The verticle zero offset value can only be set through Athlon Ballistic APP.




MOA RETICLES



#01 - MOA

1 - 20 MOA
2 - 68 MOA
3- 4 MOA


thin line - 2 px
thick line - 6 px
dot - 4 px



#02 - MOA


1 - 20 MOA
2 - 68 MOA

thin line - 2 px
thick line - 6 px



#03 - MOA


20x20 px floating cross
4px line thickness



#04 - MOA

1 - 20 MOA
2 - 35 MOA
3- 4 MOA

thin line - 2 px
thick line - 6 px
dots - 4 px




#05 - MOA

1 - 20 MOA
2 - 35 MOA
3 - 5 MOA
4 - 4 MOA
5 - 7.3 MOA
6 - 10.4 MOA
7 - 14.6 MOA

thin line - 2 px
thick line - 6 px
dots - 4 px


MIL RETICLES



#01 - MIL

1 - 2 MIL
2 - 20 MIL
3 - 10 MIL


thin line - 2 px
thick line - 4 px
dots - 4 px



#02 - MIL

1 - 5 MI L
2 - 20 MIL
3 - 1 MIL
4 - 2 MI L
5 - 2 MIL
6 - 1 MI L


thin line - 2 px
thick line - 6 p x



#03 - MIL

1 - 5 MI L
2 - 20 MIL
3 - 2.5 MIL
4 - 5 MI L
5 - 2 MIL
6 - 1 MI L


thin line - 2 px
thick line - 6 p x



#04 - MI L

1 - 2 MIL
2 - 20 MIL

thin line - 2 px
thick line - 6 px
dots - 6 px




#05 - MIL

1 - 2 MIL
2 - 10 MI L
3 - 10 MI L

thin line - 2 px
thick line - 6 px
dots - 4 px

CHAPTER 9 - BALLISTICS APP



In order to get ballistics on your thermal device, you will need to download the Athlon Ballistics app to your phone. Here you will create your rifle and bullet profiles to transmit to your thermal device.



1) Create a rifle profile.

2) Create a bullet profile.
Once the fields have been completed, clicking DONE will save your profile.


▲ NOTE: When creating these profiles, ensure you are providing accurate details in order to get accurate ballistics.



3) Turn on the thermal devices WiFi, and connect your cellular device to the thermal devices WiFi connection.



4) Open the hamburger menu and select CONNECT DEVICE.

5) Once in CONNECT DEVICE, the thermal device will be displayed. Click ENTER and then EDIT PROFILES.



6) Select the Rifle and Bullet profiles that you want to associate with the corresponding thermal Profile Configuration.

7) Clicking DONE will save the changes and transfer the data.




8) The Thermal Reticle page allows you to preview the color palettes of your main reticle, holdover reticle, as well as the crosshairs. You can fine tune the brightness and determine what ranges you want the holdovers to be at.



CHAPTER 10 - OTHER INSTRUCTIONS

10.1 POWER DISPLAY

Power Display: When the thermal scope is turned on and the battery level changes, the battery indicator is displayed in the lower left corner of the screen, and the highlighted part of the battery indicator shows the remaining battery capacity.



NOTE: When the internal battery is low, please charge it as soon as possible. The scope can not be turned on when the internal battery is out of power, and can only be turned on with external power supply through the USB-C port.

10.2 SOFTWARE CONNECTION


WiFi Connection:

- 1) Download the 'Athlon Thermal ' APP on your mobile phone;
- 2) Turn on product's WiFi via main menu
- 3) Enter the mobile phone WiFi setting, select the WiFi name of "CRONUS ATS PRO XX-xxxx", enter the password '12345678' to connect;
- 4) Return to "Athlon Thermal" APP on your mobile phone

NOTE: In order to ensure reliable Wi-Fi signal connection and stable data transmission, please keep the scope and the phone within 15 yard, and there are no obstacles (such as partition walls, etc.).

App Function Description:

Control the Scope on the APP: After the APP is successfully connected to the device's WiFi, the Scope can be remotely controlled.




Function Icons:

- ③⑥ Natural/Enhanced/Highlight mode
- ③⑦ Stadiametric Rangefinder
- ③⑧ Brightness / Contrast Adjustment
- ③⑨ Hot track, PIP, Image Enhancement
- ④⑦ Reticle Settings, Common Settings

Other Icons:

- ④① Shooting Status Display
- ④② White Hot/Black Hot/Red Hot/Iron Red/Blue Hot/Green Hot/Sepia
- ④③ Shooting/Recording Control Key
- ④④ Recording Status Display
- ④⑤ APP Gallery entry



Access files on the APP

Control the scope on the APP: After the APP is successfully connected to the device's WiFi, the scope can be remotely controlled.

- **Local album:** after the APP is connected to the scope's WIFI, the location of the file will be stored on the APP after pictures/videos are taken, and the files will be automatically saved to the local photo album of the mobile phone; the pictures/videos can be collected, shared and deleted.
- **Remote Scope:** after the APP is connected to device's WIFI, the location of the file will be stored on the APP after pictures/videos are taken; the photos/videos can be downloaded, deleted and so on. The files will be automatically saved to the local photo album of the mobile phone.
- **My Favorites:** The location where the pictures/videos are stored after they are added to my favorites.

CHAPTER 11 - FIRMWARE UPDATE


It is recommended for end users to get the latest version of firmware for improved performance and better image quality. Please follow either of the following methods to complete the update:

11.1 UPDATE VIA APP


1) Power on the thermal optic and turn on the scopes WiFi through main menu.

2) Connect the thermal optic to your mobile device using this WiFi connection.


3) Open the Athlon Thermal mobile APP and click "About Device" in the upper right corner.




4) Make sure the mobile device has cellular data connection and then tap the "Check for updates" button.





5) If there is an update available, it will appear on the screen. Tap the "Download" button and wait for 100% completion.




6) After the download is completed, tap the "Update" button to start the transferring process.




7) Once the firmware transfer is completed, the APP will show "Transfer completed!" on the top of the screen.



The screen of the thermal scope will show the options "Delete" "Cancel" and "Update." Rotate the menu knob and press the M button to select "Update."



Once the progress bar shows 100% completion, power off and on the thermal scope to begin enjoying the new firmware.



11.2 UPDATE VIA COMPUTER

1) Download the firmware package to your computer.

- To download the firmware package, visit the following URL:
<https://athlonoptics.com/thermal-firmware-update/>

Thermal Model	What's the update	Firmware Package	ASIC
CRONUS ATS PRO 35-400	Color sensitivity	V.X.X.X	V1.X.X.XXXXXXX
CRONUS ATS PRO 50-640	Color sensitivity	V.X.X.X	V1.X.X.XXXXXXX
CRONUS ATS PRO 35L-400	Color sensitivity	V.X.X.X	V1.X.X.XXXXXXX
CRONUS ATS PRO 50L-640	Color sensitivity	V.X.X.X	V1.X.X.XXXXXXX

NOTE: if you accidentally download the update package twice, please use the first download file named ota-asic.img not ota-asic(1).img. The exact file name must be used.

2) Turn on thermal device to "Com Mode."

- On the thermal device, long press the power button and M button at the same time when the device powers on, then release the power button while continuing to press the M button.
- Check the device LED screen to ensure it is in "Com Mode."

3) Connect the thermal device to your computer.

- Use type C cable to connect the thermal device to your computer.


4) Copy the downloaded firmware package to your computer.

- On your computer, copy the downloaded firmware package (ota-asic.img) to the root directory of the Thermal USB drive.
- Turn off the thermal device, then turn it back on. The firmware will update automatically.

5) Check if firmware updated successfully.

- Long press the M button until the Menu appears
- Select the Local Settings by turning M button. Go to the About screen and confirm the ASIC number matches the number listed with the update package. If it matches, then the firmware has updated successfully.

- 6) Below warning messages will be displayed if the thermal device has insufficient power, internal memory, or failed receiving and updating the firmware.



⚠ NOTE: If the updating failed and the thermal unit cannot be operated normally, please hold the M button and the power button simultaneously for 15 seconds to perform a hard power off and then power on the unit normally to restart the updating process.

CHAPTER 12 - COMMON TROUBLESHOOTING GUIDE

- 1) **The device failed to be powered on.**
Solution: Replace the battery or connect charger.
- 2) **The device has trouble taking pictures/videos.**
Solution: The internal storage space of the device is full and/or the memory card needs to be formatted.
- 3) **The time displayed on the device does not match the actual time.**
Solution: Reset the time and date of the device in the menu.
- 4) **The screen goes off during the use.**
Solution: Short press any button to wake up from sleep and light up the screen.
- 5) **Image displayed on the device is blurry during operation.**
Solution: Turn the lens to focus manually until the image is clear.
- 6) **The device is in deadlock stage and cannot be powered off normally.**
Solution: Long press the M button and the power button simultaneously for 15 seconds to have a hard power off and then power the unit on normally.



PRODUCT WARRANTY CARD

Warranty Registration Required

This product carries a 5-year warranty from the date of purchase. For your product to qualify for this warranty, you must provide proof of purchase, the model and serial number of the device. Once activated, the device is warrantied 5 years from the date of purchase.

- 1) This warranty does not cover damages caused by deliberate damage, misuse, theft or maintenance provided by someone other than the Athlon Authorized Service Department.
- 2) Please note that any altering of the products, such as Duracoat, hydro dipping or spray painting, will void the warranty on all thermal devices.

Scan the QR code to complete the online form to register your device.



**SHARP, TIGHT
AND PRICED
JUST RIGHT!**

Toll free: 1-855-913-5678

contact@athlonoptics.com

10817 RENNER BLVD,
LENEXA, KS 66219

ATHLONOPTICS.COM